

Article #: 201-222 Wireless Antimicrobial mouse, white, USB



Features and Benefits

A Medical Grade Washable, Antimicrobial 2-button Scroll IP68 wireless Optical mouse. Fully submersible, antimicrobial, washable, with silver skin antimicrobial technology. Spill safe, easy cleaning. Dishwashers save!

Main benefits are:

- Completely 100% sealed, washable and waterproof (NEMA 4X / IP68).
- Silver Antimicrobial protection (antimicrobial plastic reduces bacteria growth).
- Resistant to chemicals and disinfectants.
- 2x AAA long term batteries included
- Optical; 800 dpi resolution.
- Fast scrolling with frictionless scroll system.

Dirt & Water resistant; protects against:

| | | |
|----------------------|------------|------------|
| Water | Solvents | Salt Water |
| Disinfectants | Humidity | Abrasives |
| Dust | Corrosives | Dirt |
| Sand | Shock | Alkaline |
| Alcohol 80% | Bleach | Acid |
| Temperature Extremes | | |

Specifications

| | |
|---------------------------|---|
| Compatibility | Windows and Mac |
| Working Voltage | 3VDC +/- 10% |
| Button Life | 1 million strokes |
| Power/Interface | USB Gold-Plated, 2.4 GHz Wireless with nano USB RF receiver |
| Resolutions | 800 dpi |
| Button Press Force | 70 +/- 10g |
| Dimensions | About 114 x 70 x 38 mm |
| Weight | 80 Grams (w/o batteries and packaging) |
| Color | Black |
| Shell Material | ABS plastic |
| Agency Approvals | CE, FCC, RoHS |

Cleaning



Your Cleankeys mouse can be cleaned with:

- Hospital Grade Disinfectant
- Disinfectant Wipes
- Hand wash with soap and warm water
- Machine wash in Dishwashers

The Cleankeys mouse is designed to work with virtually all medical grade, commercial grade, antibacterial, antiviral, antifungal sprays that kill most known surface contaminants including SARS, Influenza, Staph and MRSA.

Alcohol based disinfectant wipes are the fastest and easiest way to disinfect your Cleankeys mouse.

The Cleankeys mouse is also designed to be fully immersible in water and safe to use with standard dish soap or dishwasher detergents.

FCC Compliance

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. There is no guarantee, however, that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- 1) Reorient or relocate the receiving antenna.
- 2) Increase the separation between the equipment and receiver.
- 3) Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Properly shielded and grounded cables and connectors must be used in order to meet FCC emission limits. Seal Shield, LLC, is not responsible for any radio or television interference caused by using other than recommended cables and connectors or by unauthorized changes or modifications to this equipment. Unauthorized changes or modifications could void the limited warranty.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

CAUTION: Changes or Modification not expressly approved by the manufacturer responsible for compliance could void the warranty.

Installation



4. Insert the nano receiver into an available USB port.



1. Turn the mouse over and locate the battery door.
2. Slide the retainer clamp away from the battery door until the door releases.
3. Remove the battery door and insert 2AAA alkaline batteries. Replace the cover and ensure the retainer clamp securely seals the battery door.

Installation Continued...

5. Press the Connect button on the bottom of the mouse to pair the mouse to the receiver. The mouse is now ready to use.

